

This conventional fire alarm panel has been developed to provide a simple & reliable solution to the demands of today's fire detection solution. This model is designed user friendly & cost effective. Each zone can support up to 20 number of detectors.



**22 - 8 ZONE [ 5 AMP ]CONVENTIONAL FIRE ALARM SYSTEM**

### **Features:**

- 16 \*2 Line Dot matrix LCD.
- As Per IS 2189 Standard.
- Zone wise fire, open & short LED Indications.
- Common & zone wise hooter connectivity .
- Zone wise isolation facility.
- Extra potential free contact for fire & fault.
- Reset, alarm silence, & evacuate controls etc.
- RS 485 Communication for repeater panel.
- Auto dialer attachable facility.
- Zone naming facility.
- Auto silence feature .
- Inbuilt battery charger & Battery space

### **Specifications:**

- **Operating Voltage** : Ac 220v, 50Hz + 10% voltage tolerance.
- **Operating Temperature** : 0 deg C to 50 deg C
- **Operating Humidity** : 95% [non – condensing]
- **Hooter Output** : 4 Amp, 24v DC.[ Hooter output can be increased as per customer requirement ]
- **Standby Power** : 24 VDC [ 2 No's of 12V, 7 Ah SMF Lead Acid Batteries]
- **Color** : White Structure.